

LED CANDLE

MEGAMAN® LED Candles have an even light distribution of 330° to create a comfortable lighting. The range is available with MEGAMAN® Dim to Warm emits a warmer light when dimmed, simulating the characteristics and lighting performance of incandescent lamps for creating cosy and intimate settings. Smooth and sleek finishing with all direction light emission, and an LED Candle with 360° light illumination delivers the same classic look as the incandescent lamps familiar to users.

The RichColour range allows LED Candle to offer high colour rendering of up to Ra92, which maximises the richness and quality of colours, providing a perfect LED replacement for incandescent lamps. Last but not the least, Step Dimming technology offers the flexibility to create the perfect mood for any occasion by simply pushing the ordinary on/off switch.



CANDLE / Smart Series

Dim to Warm




Equivalent Incandescent Lamp Wattage (W)	Model No.	Wattage (W)	Total Luminous Flux (lm)	Diameter (mm)	Length (mm)	Dimmable	Energy Label	Product Photo
25	LC0404w	4	250	35	100	100-10%	A+	1
25	LC0404wCS	4	250	35	100	100-10%	A+	2
40	LC1106w	6	470	40	106	100-10%	A+	3
40	LC1106wCS	6	470	40	106	100-10%	A+	4



CANDLE / Smart Series

Dimmable




Equivalent Incandescent Lamp Wattage (W)	Model No.	Wattage (W)	Total Luminous Flux (lm)	Diameter (mm)	Length (mm)	Dimmable	Energy Label	Product Photo
25	LC0403.5dv2 ¹	3.5	250	35	100	100-10%	A+	1
40	LC1106d	6	470	40	106	100-10%	A+	2



CANDLE / Smart Series

Step Dimming




Equivalent Incandescent Lamp Wattage (W)	Model No.	Wattage (W)	Total Luminous Flux (lm)	Diameter (mm)	Length (mm)	Dimmable	Energy Label
40	LC1106s	6	470	40	106	100%, 60%, 20%	A+

Please refer to the website www.megaman.cc/user-guide for the compatible dimmer list. E27 lamp base is available for Candle with 400lm or above.
¹ Preliminary Data



CANDLE / Smart Series

360° illumination



Equivalent Incandescent Lamp Wattage (W)	Model No.	Wattage (W)	Total Luminous Flux (lm)	Diameter (mm)	Length (mm)	Dimmable	Energy Label
25	LC2003 ¹	NEW 3	250	35	98	No	A++



CANDLE / Smart Series

RichColour Ra92



Equivalent Incandescent Lamp Wattage (W)	Model No.	Wattage (W)	Total Luminous Flux (lm)	Diameter (mm)	Length (mm)	Dimmable	Energy Label
25	LC0403.5R9v2 ¹	NEW 3.5	250	35	100	No	A+
40	LC0405.5R9 ¹	NEW 5.5	470	35	100	No	A+



CANDLE / Economy Series



Equivalent Incandescent Lamp Wattage (W)	Model No.	Wattage (W)	Total Luminous Flux (lm)	Diameter (mm)	Length (mm)	Dimmable	Energy Label
15	LC0402	2	136	35	100	No	A+
25	LC0403.5v2	3.5	250	35	100	No	A+
29	LC0405 ¹	NEW 5	320	35	100	No	A+
40	LC0405.5	5.5	470	35	100	No	A+

Please refer to the website www.megaman.cc/user-guide for the compatible dimmer list.

E27 lamp base is available for Candle with 400lm or above.

¹ Preliminary Data