

## GDS736v0

## TECHNICAL DOCUMENT- CONTROL GEAR

Supplier's name or trade mark:	MEGAMAN GmbH
Supplier's address	Halskestraße 22-26, AircomParc A140880 RatingenGermany

**Model identifier**

Model Number	GDS736v0
General description	Input: AC220~240 Output: 1.5W DC22 AC220~240mA

**Technical Document**

Maximum output power	1.5W
Type of light source(s)	LED
Efficiency in full-load	75%
No-load power (Pno)	not applicable
Standby Power (Psb)	N/A
Networked Standby Power (Pnet)	N/A
Outer dimensions in mm	
Height	8
Width	52
Depth	52
Mass in grams	5.4
Standards Compliance	EN 61347-1:2015 & EN61347-2-13:2014

**Warning**

A list of compatible dimmers shall be provided on the website [www.megaman.cc](http://www.megaman.cc)

MEGAMAN | WEEE - Green Room | LED, Energy-efficient & Eco-friendly Lighting, Restriction of Hazardous Substance  
<https://www.megaman.cc/resources/green-room/weee>

**Identification and signature**

Model no.:FDS73600v0, FDS73600v0-sc

Light source model identifier:SDS736v0830,SDS736v0840,SDS736v0sc830840

Light source: Removable

SDS736v0830,SDS736v0840,SDS736v0sc830840

I in: 22mA U in 220VAC

Step 1: Use a screwdriver to pry open along the gap between the base and the ring



Step 2: Separate the light source and driver.

