






Perfect White LED AR111

Key	
1 to 2	Compatible, with one to two lamps
	The transformer is not tested or not recommended

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2712p-75H24D & ER2912p-75H45D
				
Actec	MINI60	230-240	20-60	1 to 1
Allttx	MT60	230	60	1 to 1
Anchorn	AET-3502R1	220-240	35-150	1 to 2
Andawo	MR-128	220	20-50	1 to 1
Atom	Tiger	230-240	20-60	1 to 1
Aurora	AU-E60	240	10-60	1 to 1
Barrow	TED20600209-100310	220	60	1 to 1
BAW	TREH60C1 6-60w	220	60	1 to 1
Click	TR060	240	20-60	1 to 1
Collingwood	SKY I 60	240	20-60	1 to 1
Dais	DA-J60	240	20-60	1 to 1
Dura	DELT12060P	230	20-60	1 to 1
Dura	DELT12105M	220-240	35-105	1 to 2
Eico	E60W	220-240	10-60	1 to 1
EMC	ET105	230	35-105	1 to 2
EMC Sp. z o.o	YT70	230	0-70	1 to 1
Emcolite	EMRED60	240	20-60	1 to 1
Enlite	EN-SC60	240	20-60	1 to 1
Flash Light	HA-105	220-240	35-105	1 to 2
Flash Light	HA-60	220-240	20-60	1 to 1

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2712p-75H24D & ER2912p-75H45D	
					
Generic	TE12/70 CODE SB1240-B	220-240	10-70	1 to 1	
Geni	GT-006	170-240	60	1 to 1	
Gira	Tronic-Trafo 0366 00	230	20-70	1 to 1	
Gira	Tronic-Trafo 0371 00	230-240	20-105	1 to 2	
Gira	Tronic-Trafo 0378 00	230-240	20-105	1 to 2	
Group	TB60I 230 10-60W	230	10-60	1 to 1	
Group	TE105S 20-105W	230-240	20-105	1 to 1	
Group	TE70S 10-70W	230-240	10-70	1 to 1	
Group	TL150S 50-150W	230-240	50-150	1 to 2	
Halolite	HA-S105	240	35-105	1 to 2	
Halolite	HA-S60TA	220-240	20-60	1 to 1	
Halolite	HA-SE60	240	20-60	1 to 1	
Horoz	HL317	220	105	1 to 2	
JCC	JC4030(10-60AV)	220-240	10-60	1 to 1	
Kengo	DET-60S	220-240	10-60	1 to 1	
Kengo	Ket105	230-240	35-105	1 to 2	
Light Division	ET60A	230	20-60	1 to 1	
Lightech	LET 75/12V	230-240	20-75	1 to 1	
Lightron	ETH-55Eco	240	50	1 to 1	
Lite Beetle	LET 105/240LB	240	35-105	1 to 1	
Lite-Tech	SY1507/W	220-240	20-60	1 to 1	
Lival	Pico Wolf 70	220-240	70	1 to 1	
Loretto	LT60	220-240	20-60	1 to 1	
Meek	ET-60W	230	60	1 to 1	
MP Lamp	T60	220-240	10-60	1 to 1	
Niko	320-00121	230	20-70	1 to 1	

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2712p-75H24D & ER2912p-75H45D	
					
Nobile	EN-110D2	230	35-110	1 to 2	
NVC	ET60E	220	20-60	1 to 1	
Online	Pico Wolf 60	230-240	10-60	1 to 1	
Online	Pico Wolf 70	230-240	70	1 to 1	
Osram	ET-A 60/220-240	220-240	20-60	1 to 1	
Osram	ET-PARROT 105/240 I	240	35-105	2 to 2	
Osram	ET-PARROT 70/220-240 I	220-240	20-70	1 to 1	
Osram	ET-REDBACK 60VA/230-240	230-240	20-60	1 to 1	
Osram	Halotronic HTM 150/230-240	230-240	50-105	1 to 2	
Osram	Halotronic HTM 70/230-240	230-240	20-70	1 to 1	
Osram	IZ-A 50/240	240	50	1 to 1	
Osram	IZ-HALO 50/220-240	220-240	20-50	1 to 1	
Philips	Certaline 60w	230	20-60	1 to 1	
Philips	EHC 075 S	230	20-75	1 to 1	
Philips	EHC250 F	220	35-60	1 to 1	
Philips	ET-E 60 220-240	220-240	20-60	1 to 1	
Philips	ET-S 150 220-240	220-240	35-105	1 to 2	
Philips	Primaline 105 230-240	230-240	35-105	1 to 2	
Philips	Primaline 150 230-240	230-240	50-150	1 to 2	
Philips	Primaline 70 230-240	230-240	20-70	1 to 1	
Puma	ET-075P-230-RD	230-240	35-75	1 to 1	
QLT	T105K	230	35-105	1 to 2	
QLT	W60	230	20-60	1 to 1	
Releo	Micro 60 PFS	230-240	10-60	1 to 1	
Robus	LDT150N	230-240	35-150	1 to 2	
Robus	LT60d	240	20-60	1 to 1	

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2712p-75H24D & ER2912p-75H45D	
					
Sector	ALVT60ED	240	20-60	1 to 1	
Self	SET105F-2	230	35-105	1 to 2	
Self	SET70F-2	230	20-70	1 to 1	
Sylvania	MINI 60	220-240	20-60	1 to 1	
TAO	TET-E60I	220	60	1 to 1	
TCI	MW 70 LED	230-240	1-70	1 to 1	
TCI	Pico Wolf 60 V.2	230-240	10-60	1 to 1	
TCI	SHARK60	220-240	10-60	1 to 1	
Tridonic	22176072	230-240	60	1 to 1	
Tridonic	22176074	230-240	105	2 to 2	
Tridonic	22176110	230	60	1 to 1	
Tridonic	Atco 22176070	230-240	60	1 to 1	
Tridonic	Atco TE-0105 S003	230-240	105	1 to 2	
Unotech	UD-105	220-240	35-105	1 to 2	
Unotech	UD-60	220-240	20-60	1 to 1	
Ushio Group	456001	230	0-60	1 to 1	

Remarks:

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the halogen transformer, which is subject to the status of the manufacturer's technology. Due to possible variations in country halogen transformer module specifications, please contact your local distributor for a list of compatible halogen transformers before installation.
 Copyright © MEGAMAN® 2015. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
 All other trademarks mentioned are the property of their respective owners.