




## LED MR11


Key	
1 to 6	Compatible, with one to six lamps
	The transformer is not tested or not recommended

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2304-20H36D
				
Actec	MINI60	230-240	20-60	1 to 3
Actec	VENUS60	230-240	20-60	2 to 3
Allttx	MT60	230	20-60	1 to 2
Anchorn	AET-3502R1	220-240	35-150	1 to 6
Andawo	MR-128	220	20-50	1 to 2
Atom	Tiger	230-240	20-60	1 to 3
Aurora	AU-E60	240	10-60	1 to 2
Barrow	TED20600209-100310	220	20-60	2 to 3
BAW	TREH60C1 6-60w	220	6-60	1 to 3
Click	TR060	240	20-60	3 to 3
Collingwood	SKY I 60	240	20-60	2 to 3
Dais	DA-J60	240	20-60	1 to 3
Dura	DELT12060P	230	20-60	1 to 3
Dura	DELT12105M	220-240	35-105	1 to 5
Eico	E60W	220-240	10-60	1 to 3

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2304-20H36D
				
ELT	TCE 5/23-E	230-240	20-50	1 to 2
ELT	TR 5/23-01-SC	230	50	1 to 2
EMC	ET105	230	35-105	1 to 5
Emcolite	EMRED60	240	20-60	2 to 3
Enlite	EN-SC60	240	20-60	2 to 2
ERC	TRAEK02	230	20-60	1 to 3
Eterna	T60VA	240	20-60	2 to 3
FLC	ET60A	230	3-60	1 to 3
Generic	TE12/70 CODE SB1240-B	220-240	70	1 to 3
Geni	GT-006	170-240	60	1 to 3
Halolite	HA-S105	240	35-105	1 to 2
HEP Group	TE105S 20-105W	230-240	20-105	1 to 5
HEP Group	TE70S 10-70W	230-240	10-70	1 to 3
HEP Group	TR70 10-70W	230	10-70	1 to 3
Horoz	HL317	220	105	1 to 2
JCC	JC4030(10-60AV)	220-240	10-60	2 to 3
Kengo	Ket105	230-240	35-105	1 to 5
Lightron	ETH-55Eco	240	50	1 to 2
Lival	Pico Wolf 70	220-240	20-70	1 to 3
Loretto	LT60	220-240	20-60	1 to 2

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2304-20H36D
				
Lucci	TB60L 240 10-60W	240	10-60	1 to 3
Massgrove	MT60	240	20-60	3 to 3
Meek	ET-60W	230	60	1 to 3
MP Lamp	T60	220-240	10-60	1 to 3
Niko	320-00121	230	20-70	1 to 3
Nobile	EN-110D2	230	35-110	1 to 5
NVC	ET60E	220	20-60	1 to 3
Online	Pico Wolf 70	230-240	20-70	1 to 2
Orbit Lighting	LET60B	240	10-60	1 to 3
Osram	ET-LED 30/220-240	220-240	2-30	1 to 1
Osram	ET-P 60/220-240	220-240	20-60	2 to 3
Osram	ET-Z 60/220-240	220	20-60	1 to 3
Osram	Halotronic HTM 150/230-240	230-240	50-150	1 to 6
Osram	Halotronic HTM 70/230-240	230-240	20-70	3 to 3
Osram	IZ-A 50/240	240	50	1 to 2
Osram	IZ-HALO 50/220-240	220-240	20-50	1 to 2
Philips	Certaline 60w	230	20-60	3 to 3
Philips	EHC 075 S	230	20-75	1 to 3
Philips	ET50 220/12V	170-250	40-60	1 to 3
Philips	ET-E60 220-240	220-240	20-60	1 to 3

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2304-20H36D
				
Philips	Primaline 70 230-240	230-240	20-70	1 to 3
Puma	ET-075P-230-RD	230-240	35-75	1 to 3
Radium	ET-RALOPOWER	230-240	20-60	1 to 3
Reico	RN1613	230-240	100-160	1 to 5
Releo	MICRO 60 PFS	230-240	10-60	1 to 1
RIO	RT060CP	220V	60	1 to 3
Robus	LT60d	240	20-60	1 to 3
Robus	RM70DN	220-240	20-70	1 to 3
Sector	ALVT60ED	240	20-60	1 to 3
Self	SET105F-2	230	35-105	1 to 1
Self	SET70F-2	230	20-70	1 to 3
Self	SET70R	220-240	20-70	1 to 3
Skytronic	VWY-006	170-250	20	1 to 1
Sylvania	MINI 60	220-240	20-60	1 to 3
TAO	SET150-2	230	50-150	2 to 6
TAO	TET-E60I	220	20-60	1 to 3
TCI	MW 70 LED	230-240	1-70	2 to 2
TED	WIN-60SLV	220-240	10-60	2 to 3
Tridonic	Atco TE-0105 S003	230-240	105	2 to 2
Tridonic	Atco Viper 60VA 22176070	230-240	60	1 to 3

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2304-20H36D
				
Tridonic	Speedy TE-0105 C101	230-240	35-105	1 to 5
Tridonic	Viper 105 22176074	230-240	105	1 to 5
Tridonic	Viper 60VA 22176110	230	60	1 to 3
Unotech	UD-105	220-240	35-105	1 to 1
Ushio Group	456001	230	0-60	1 to 3
Voitwell	V3YB-50-B	220	20-50	2 to 2

**Remarks:**

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the halogen transformer, which is subject to the status of the manufacturer's technology. Due to possible variations in country halogen transformer module specifications, please contact your local distributor for a list of compatible halogen transformers before installation.  
 Copyright © MEGAMAN® 2016. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.  
 All other trademarks mentioned are the property of their respective owners.